

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
B5817W	20	1.0	0.45	1.0	1000	20	SOD-123
B5818W	30	1.0	0.55	1.0	1000	30	SOD-123
B5819W	40	1.0	0.60	1.0	1000	40	SOD-123
B0520W	20	0.5	0.39	0.5	250	20	SOD-123
B0530W	30	0.5	0.43	0.5	130	30	SOD-123
B0540W	40	0.5	0.51	0.5	20	40	SOD-123
SD103AW	40	0.2	0.60	0.2	5.0	30	SOD-123
SD103BW	30	0.2	0.60	0.2	5.0	20	SOD-123
SD103CW	20	0.2	0.60	0.2	5.0	10	SOD-123
BAT46W	100	0.15	0.45	0.01	2.0	75	SOD-123
BAT54W	30	0.2	1.00	0.1	2.0	25	SOD-123
B5817WS	20	1.0	0.45	1.0	1000	20	SOD-323
B5818WS	30	1.0	0.55	1.0	1000	30	SOD-323
B5819WS	40	1.0	0.60	1.0	1000	40	SOD-323
B16WS	60	1.0	0.70	1.0	100	60	SOD-323
K1AWS	100	1.0	0.85	1.0	100	100	SOD-323
B0520WS	20	0.5	0.39	0.5	250	20	SOD-323
B0530WS	30	0.5	0.43	0.5	130	30	SOD-323
B0540WS	40	0.5	0.51	0.5	20	40	SOD-323
SD103AWS	40	0.2	0.60	0.2	5.0	30	SOD-323
SD103BWS	30	0.2	0.60	0.2	5.0	20	SOD-323
SD103CWS	20	0.2	0.60	0.2	5.0	10	SOD-323
BAT46WS	100	0.15	0.45	0.01	2.0	75	SOD-323
BAT54WS	30	0.2	1.00	0.1	2.0	25	SOD-323
RB550V-30	30	1.0	0.52	1.0	30	10	SOD-323
RB551V-30	30	0.5	0.47	0.5	100	20	SOD-323
RB551V-40	40	0.5	0.47	0.5	100	40	SOD-323
RB751V-40	40	0.03	0.37	0.001	0.5	30	SOD-323
BAT42WS	30	0.2	1.00	0.2	10	25	SOD-323
BAS40WS	40	0.2	1.00	0.04	0.2	30	SOD-323
SOD103AWT	40	0.35	0.60	0.2	5.0	30	SOD-523
RB520S-30	30	0.2	0.60	0.2	1.0	10	SOD-523
RB520S-40	40	0.2	0.55	0.1	1.0	10	SOD-523
RB521S-40	40	0.2	0.54	0.2	90	40	SOD-523
RB751S-40	40	0.03	0.37	0.001	0.5	30	SOD-523
BAS40	40	0.2	1.0	0.04	0.2	30	SOT-23
BAS40-04	40	0.2	1.0	0.04	0.2	30	SOT-23
BAS40-05	40	0.2	1.0	0.04	0.2	30	SOT-23
BAS40-06	40	0.2	1.0	0.04	0.2	30	SOT-23
BAT54	30	0.1	1.0	0.1	2.0	25	SOT-23
BAT54A	30	0.1	1.0	0.1	2.0	25	SOT-23

Schottky Diodes 肖特基二极管

Part Number	V_{RRM} (V)	I_O (A)	V_F (V)		I_R (μ A)		Package
			Max.	I_F (A)	Max.	V_R (V)	
BAT54C	30	0.1	1.0	0.1	2.0	25	SOT-23
BAT54S	30	0.1	1.0	0.1	2.0	25	SOT-23
1SS344	20	0.5	0.55	0.5	100	20	SOT-23
K14	40	1.0	0.55	1.0	100	40	SOD-123FL
K16	60	1.0	0.70	1.0	100	60	SOD-123FL
K110	100	1.0	0.85	1.0	50	100	SOD-123FL
K115	150	1.0	0.95	1.0	50	150	SOD-123FL
K120	200	1.0	0.95	1.0	50	200	SOD-123FL
K24	40	2.0	0.55	2.0	100	40	SOD-123FL
K26	60	2.0	0.70	2.0	100	60	SOD-123FL
K210	100	2.0	0.85	2.0	50	100	SOD-123FL
K215	150	2.0	0.95	2.0	50	150	SOD-123FL
K220	200	2.0	0.95	2.0	50	200	SOD-123FL
K34	40	3.0	0.55	3.0	100	40	SOD-123FL
K36	60	3.0	0.70	3.0	100	60	SOD-123FL
K310	100	3.0	0.85	3.0	50	100	SOD-123FL
K315	150	3.0	0.95	3.0	50	150	SOD-123FL
K320	200	3.0	0.95	3.0	50	200	SOD-123FL
SS12A	20	1.0	0.50	1.0	100	20	SMA
SS14A	40	1.0	0.55	1.0	100	40	SMA
SS16A	60	1.0	0.70	1.0	100	60	SMA
SS110A	100	1.0	0.85	1.0	50	100	SMA
SS115A	150	1.0	0.95	1.0	50	150	SMA
SS120A	200	1.0	0.95	1.0	50	200	SMA
SS24A	40	2.0	0.55	2.0	100	40	SMA
SS26A	60	2.0	0.70	2.0	100	60	SMA
SS210A	100	2.0	0.85	2.0	50	100	SMA
SS215A	150	2.0	0.95	2.0	50	150	SMA
SS220A	200	2.0	0.95	2.0	50	200	SMA
SS34A	40	3.0	0.55	3.0	100	40	SMA
SS36A	60	3.0	0.70	3.0	100	60	SMA
SS310A	100	3.0	0.85	3.0	50	100	SMA
SS315A	150	3.0	0.95	3.0	50	150	SMA
SS320A	200	3.0	0.95	3.0	50	200	SMA
SS54A	40	5.0	0.55	5.0	100	40	SMA
SS56A	60	5.0	0.70	5.0	100	60	SMA
SS510A	100	5.0	0.85	5.0	50	100	SMA
SS515A	150	5.0	0.95	5.0	50	150	SMA
SS520A	200	5.0	0.95	5.0	50	200	SMA
SS14F	40	1.0	0.55	1.0	100	40	SMAF
SS16F	60	1.0	0.70	1.0	100	60	SMAF

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
SS110F	100	1.0	0.85	1.0	50	100	SMAF
SS115F	150	1.0	0.95	1.0	50	150	SMAF
SS120F	200	1.0	0.95	1.0	50	200	SMAF
SS24F	40	2.0	0.55	2.0	100	40	SMAF
SS26F	60	2.0	0.70	2.0	100	60	SMAF
SS210F	100	2.0	0.85	2.0	50	100	SMAF
SS215F	150	2.0	0.95	2.0	50	150	SMAF
SS220F	200	2.0	0.95	2.0	50	200	SMAF
SS34F	40	3.0	0.55	3.0	100	40	SMAF
SS36F	60	3.0	0.70	3.0	100	60	SMAF
SS310F	100	3.0	0.85	3.0	50	100	SMAF
SS315F	150	3.0	0.95	3.0	50	150	SMAF
SS320F	200	3.0	0.95	3.0	50	200	SMAF
SS54F	40	5.0	0.55	5.0	100	40	SMAF
SS56F	60	5.0	0.70	5.0	100	60	SMAF
SS510F	100	5.0	0.85	5.0	50	100	SMAF
SS515F	150	5.0	0.95	5.0	50	150	SMAF
SS520F	200	5.0	0.95	5.0	50	200	SMAF
SS24B	40	2.0	0.55	2.0	100	40	SMB
SS26B	60	2.0	0.70	2.0	100	60	SMB
SS210B	100	2.0	0.85	2.0	50	100	SMB
SS215B	150	2.0	0.95	2.0	50	150	SMB
SS220B	200	2.0	0.95	2.0	50	200	SMB
SS34B	40	3.0	0.55	3.0	100	40	SMB
SS36B	60	3.0	0.70	3.0	100	60	SMB
SS310B	100	3.0	0.85	3.0	50	100	SMB
SS315B	150	3.0	0.95	3.0	50	150	SMB
SS320B	200	3.0	0.95	3.0	50	200	SMB
SS54B	40	5.0	0.55	5.0	100	40	SMB
SS56B	60	5.0	0.70	5.0	100	60	SMB
SS510B	100	5.0	0.85	5.0	50	100	SMB
SS515B	150	5.0	0.95	5.0	50	150	SMB
SS520B	200	5.0	0.95	5.0	50	200	SMB
SS84B	40	8.0	0.55	8.0	100	40	SMB
SS86B	60	8.0	0.70	8.0	100	60	SMB
SS810B	100	8.0	0.85	8.0	50	100	SMB
SS815B	150	8.0	0.95	8.0	50	150	SMB
SS820B	200	8.0	0.95	8.0	50	200	SMB
SS24BF	40	2.0	0.55	2.0	100	40	SMBF
SS26BF	60	2.0	0.70	2.0	100	60	SMBF
SS210BF	100	2.0	0.85	2.0	50	100	SMBF

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
SS215BF	150	2.0	0.95	2.0	50	150	SMBF
SS220BF	200	2.0	0.95	2.0	50	200	SMBF
SS34BF	40	3.0	0.55	3.0	100	40	SMBF
SS36BF	60	3.0	0.70	3.0	100	60	SMBF
SS310BF	100	3.0	0.85	3.0	50	100	SMBF
SS315BF	150	3.0	0.95	3.0	50	150	SMBF
SS320BF	200	3.0	0.95	3.0	50	200	SMBF
SS54BF	40	5.0	0.55	5.0	100	40	SMBF
SS56BF	60	5.0	0.70	5.0	100	60	SMBF
SS510BF	100	5.0	0.85	5.0	50	100	SMBF
SS515BF	150	5.0	0.95	5.0	50	150	SMBF
SS520BF	200	5.0	0.95	5.0	50	200	SMBF
SS84BF	40	8.0	0.55	8.0	100	40	SMBF
SS86BF	60	8.0	0.70	8.0	100	60	SMBF
SS810BF	100	8.0	0.85	8.0	50	100	SMBF
SS815BF	150	8.0	0.95	8.0	50	150	SMBF
SS820BF	200	8.0	0.95	8.0	50	200	SMBF
SS34C	40	3.0	0.55	3.0	100	40	SMC
SS36C	60	3.0	0.70	3.0	100	60	SMC
SS310C	100	3.0	0.85	3.0	50	100	SMC
SS315C	150	3.0	0.95	3.0	50	150	SMC
SS320C	200	3.0	0.95	3.0	50	200	SMC
SS54C	40	5.0	0.55	5.0	100	40	SMC
SS56C	60	5.0	0.70	5.0	100	60	SMC
SS510C	100	5.0	0.85	5.0	50	100	SMC
SS515C	150	5.0	0.95	5.0	50	150	SMC
SS520C	200	5.0	0.95	5.0	50	200	SMC
SS84C	40	8.0	0.55	8.0	200	40	SMC
SS86C	60	8.0	0.70	8.0	200	60	SMC
SS810C	100	8.0	0.85	8.0	50	100	SMC
SS815C	150	8.0	0.95	8.0	50	150	SMC
SS820C	200	8.0	0.95	8.0	50	200	SMC
SS1045C	45	10.0	0.55	10.0	200	45	SMC
SS1060C	60	10.0	0.70	10.0	200	60	SMC
SS10100C	100	10.0	0.85	10.0	50	100	SMC
SS10150C	150	10.0	0.95	10.0	50	150	SMC
SS10200C	200	10.0	0.95	10.0	50	200	SMC
SP1045	45	10.0	0.55	10.0	200	45	TO-277
SP1060	60	10.0	0.70	10.0	200	60	TO-277
SP10100	100	10.0	0.85	10.0	50	100	TO-277
SP10150	150	10.0	0.95	10.0	50	150	TO-277

Schottky Diodes 肖特基二极管

Part Number	V_{RRM} (V)	I_O (A)	V_F (V)		I_R (μ A)		Package
			Max.	I_F (A)	Max.	V_R (V)	
SP10200	200	10.0	0.95	10.0	50	200	TO-277
SP10300	300	10.0	0.98	10.0	50	300	TO-277
SP2045	45	20.0	0.55	20.0	200	45	TO-277
SP2060	60	20.0	0.70	20.0	200	60	TO-277
SP20100	100	20.0	0.85	20.0	50	100	TO-277
SP20150	150	20.0	0.95	20.0	50	150	TO-277
SP20200	200	20.0	0.95	20.0	50	200	TO-277
SP1045L	45	10.0	0.45	10.0	200	45	TO-277
SP1060L	60	10.0	0.62	10.0	200	60	TO-277
SP10100L	100	10.0	0.68	10.0	50	100	TO-277
SP10U100L	100	10.0	0.66	10.0	50	100	TO-277
SP10150L	150	10.0	0.80	10.0	50	150	TO-277
SP10200L	200	10.0	0.80	10.0	50	200	TO-277
SP10300L	300	10.0	0.85	10.0	50	300	TO-277
SP1545L	45	15.0	0.46	15.0	200	45	TO-277
SP1580L	80	15.0	0.75	15.0	50	80	TO-277
SP15100L	100	15.0	0.68	15.0	50	100	TO-277
SP2045L	45	20.0	0.50	20.0	200	45	TO-277
SP2080L	80	20.0	0.65	20.0	100	80	TO-277
SP20100L	100	20.0	0.68	15.0	80	100	TO-277
MBR545DS	45	5.0	0.55	10.0	100	45	TO-252
MBR560DS	60	5.0	0.70	5.0	100	60	TO-252
MBR5100DS	100	5.0	0.85	5.0	50	100	TO-252
MBR5150DS	150	5.0	0.95	5.0	50	150	TO-252
MBR5200DS	200	5.0	0.95	5.0	50	200	TO-252
MBR845DS	45	8.0	0.55	8.0	200	45	TO-252
MBR860DS	60	8.0	0.70	8.0	200	60	TO-252
MBR8100DS	100	8.0	0.85	8.0	50	100	TO-252
MBR8150DS	150	8.0	0.95	8.0	50	150	TO-252
MBR8200DS	200	8.0	0.95	8.0	50	200	TO-252
MBR1045DS	45	10.0	0.55	10.0	200	45	TO-252
MBR1060DS	60	10.0	0.70	10.0	200	60	TO-252
MBR10100DS	100	10.0	0.85	10.0	50	100	TO-252
MBR10150DS	150	10.0	0.95	10.0	50	150	TO-252
MBR10200DS	200	10.0	0.95	10.0	50	200	TO-252
MBR2045DS	45	20.0	0.65	20.0	200	45	TO-252
MBR2060DS	60	20.0	0.70	20.0	200	60	TO-252
MBR20100DS	100	20.0	0.85	20.0	50	100	TO-252
MBR20150DS	150	20.0	0.95	20.0	50	150	TO-252
MBR20200DS	200	20.0	0.95	20.0	50	200	TO-252
MBR1045CS	45	10.0	0.65	5.0	200	45	TO-252

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
MBR1060CS	60	10.0	0.70	5.0	200	60	TO-252
MBR10100CS	100	10.0	0.85	5.0	50	100	TO-252
MBR10150CS	150	10.0	0.95	5.0	50	150	TO-252
MBR10200CS	200	10.0	0.95	5.0	50	200	TO-252
MBR2045CS	45	20.0	0.65	10.0	200	45	TO-252
MBR2060CS	60	20.0	0.70	10.0	200	60	TO-252
MBR20100CS	100	20.0	0.85	10.0	50	100	TO-252
MBR20150CS	150	20.0	0.95	10.0	50	150	TO-252
MBR20200CS	200	20.0	0.95	10.0	50	200	TO-252
1K4	40	1.0	0.55	1.0	100	40	R-1
1K6	60	1.0	0.70	1.0	100	60	R-1
1K10	100	1.0	0.85	1.0	50	100	R-1
1K15	150	1.0	0.95	1.0	50	150	R-1
1K20	200	1.0	0.95	1.0	50	200	R-1
SR140	40	1.0	0.55	1.0	100	40	DO-41
SR160	60	1.0	0.70	1.0	100	60	DO-41
SR1100	100	1.0	0.85	1.0	50	100	DO-41
SR1150	150	1.0	0.95	1.0	50	150	DO-41
SR1200	200	1.0	0.95	1.0	50	200	DO-41
1N5817	20	1.0	0.46	1.0	100	20	DO-41
1N5818	30	1.0	0.55	1.0	100	30	DO-41
1N5819	40	1.0	0.55	1.0	50	40	DO-41
SR240	40	2.0	0.55	2.0	100	40	DO-15
SR260	60	2.0	0.70	2.0	100	60	DO-15
SR2100	100	2.0	0.85	2.0	50	100	DO-15
SR2150	150	2.0	0.95	2.0	50	150	DO-15
SR2200	200	2.0	0.95	2.0	50	200	DO-15
SR340	40	3.0	0.55	3.0	100	40	DO-27
SR360	60	3.0	0.70	3.0	100	60	DO-27
SR3100	100	3.0	0.85	3.0	50	100	DO-27
SR3150	150	3.0	0.95	3.0	50	150	DO-27
SR3200	200	3.0	0.95	3.0	50	200	DO-27
SR540	40	5.0	0.55	5.0	100	40	DO-27
SR560	60	5.0	0.70	5.0	100	60	DO-27
SR5100	100	5.0	0.85	5.0	50	100	DO-27
SR5150	150	5.0	0.95	5.0	50	150	DO-27
SR5200	200	5.0	0.95	5.0	50	200	DO-27
SR840	40	8.0	0.55	8.0	100	40	DO-27
SR860	60	8.0	0.70	8.0	100	60	DO-27
SR8100	100	8.0	0.85	8.0	50	100	DO-27
SR8150	150	8.0	0.95	8.0	50	150	DO-27

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
SR8200	200	8.0	0.95	8.0	50	200	DO-27
SR1040	40	10.0	0.55	10.0	100	40	DO-27
SR1060	60	10.0	0.70	10.0	100	60	DO-27
SR10100	100	10.0	0.85	10.0	50	100	DO-27
SR10150	150	10.0	0.95	10.0	50	150	DO-27
SR10200	200	10.0	0.95	10.0	50	200	DO-27
MBR1045CT	45	10.0	0.65	5.0	200	45	TO-220AB
MBR1060CT	60	10.0	0.70	5.0	200	60	TO-220AB
MBR10100CT	100	10.0	0.85	5.0	50	100	TO-220AB
MBR10150CT	150	10.0	0.95	5.0	50	150	TO-220AB
MBR10200CT	200	10.0	0.95	5.0	50	200	TO-220AB
MBR2045CT	45	20.0	0.65	10.0	200	45	TO-220AB
MBR2060CT	60	20.0	0.70	10.0	200	60	TO-220AB
MBR20100CT	100	20.0	0.85	10.0	50	100	TO-220AB
MBR20150CT	150	20.0	0.95	10.0	50	150	TO-220AB
MBR20200CT	200	20.0	0.95	10.0	50	200	TO-220AB
MBR3045CT	45	30.0	0.65	15.0	200	45	TO-220AB
MBR3060CT	60	30.0	0.70	15.0	200	60	TO-220AB
MBR30100CT	100	30.0	0.85	15.0	50	100	TO-220AB
MBR30150CT	150	30.0	0.95	15.0	50	150	TO-220AB
MBR30200CT	200	30.0	0.95	15.0	50	200	TO-220AB
MBR4045CT	45	40.0	0.65	20.0	200	45	TO-220AB
MBR4060CT	60	40.0	0.70	20.0	200	60	TO-220AB
MBR40100CT	100	40.0	0.85	20.0	50	100	TO-220AB
MBR40150CT	150	40.0	0.95	20.0	50	150	TO-220AB
MBR40200CT	200	40.0	0.95	20.0	50	200	TO-220AB
MBR1045FCT	45	10.0	0.65	5.0	200	45	ITO-220AB
MBR1060FCT	60	10.0	0.70	5.0	200	60	ITO-220AB
MBR10100FCT	100	10.0	0.85	5.0	50	100	ITO-220AB
MBR10150FCT	150	10.0	0.95	5.0	50	150	ITO-220AB
MBR10200FCT	200	10.0	0.95	5.0	50	200	ITO-220AB
MBR2045FCT	45	20.0	0.65	10.0	200	45	ITO-220AB
MBR2060FCT	60	20.0	0.70	10.0	200	60	ITO-220AB
MBR20100FCT	100	20.0	0.85	10.0	50	100	ITO-220AB
MBR20150FCT	150	20.0	0.95	10.0	50	150	ITO-220AB
MBR20200FCT	200	20.0	0.95	10.0	50	200	ITO-220AB
MBR3045FCT	45	30.0	0.65	15.0	200	45	ITO-220AB
MBR3060FCT	60	30.0	0.70	15.0	200	60	ITO-220AB
MBR30100FCT	100	30.0	0.85	15.0	50	100	ITO-220AB
MBR30150FCT	150	30.0	0.95	15.0	50	150	ITO-220AB
MBR30200FCT	200	30.0	0.95	15.0	50	200	ITO-220AB

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
MBR4045FCT	45	40.0	0.65	20.0	200	45	ITO-220AB
MBR4060FCT	60	40.0	0.70	20.0	200	60	ITO-220AB
MBR40100FCT	100	40.0	0.85	20.0	50	100	ITO-220AB
MBR40150FCT	150	40.0	0.95	20.0	50	150	ITO-220AB
MBR40200FCT	200	40.0	0.95	20.0	50	200	ITO-220AB
MBR10100DC	100	10.0	0.85	5.0	50	100	ITO-220AB
MBR10150DC	150	10.0	0.95	5.0	50	150	ITO-220AB
MBR10200DC	200	10.0	0.95	5.0	50	200	ITO-220AB
MBR2045DC	45	20.0	0.65	10.0	200	45	ITO-220AB
MBR2060DC	60	20.0	0.70	10.0	200	60	ITO-220AB
MBR20100DC	100	20.0	0.85	10.0	50	100	ITO-220AB
MBR20150DC	150	20.0	0.95	10.0	50	150	ITO-220AB
MBR20200DC	200	20.0	0.95	10.0	50	200	ITO-220AB
MBR3045DC	45	30.0	0.65	15.0	200	45	ITO-220AB
MBR3060DC	60	30.0	0.70	15.0	200	60	ITO-220AB
MBR30100DC	100	30.0	0.85	15.0	50	100	ITO-220AB
MBR30150DC	150	30.0	0.95	15.0	50	150	ITO-220AB
MBR30200DC	200	30.0	0.95	15.0	50	200	ITO-220AB
MBR4045DC	45	40.0	0.65	20.0	200	45	ITO-220AB
MBR4060DC	60	40.0	0.70	20.0	200	60	ITO-220AB
MBR40100DC	100	40.0	0.85	20.0	50	100	ITO-220AB
MBR40150DC	150	40.0	0.95	20.0	50	150	ITO-220AB
MBR40200DC	200	40.0	0.95	20.0	50	200	ITO-220AB
MBR3045PTS	45	30.0	0.65	15.0	200	45	TO-247S
MBR3060PTS	60	30.0	0.70	15.0	200	60	TO-247S
MBR30100PTS	100	30.0	0.85	15.0	50	100	TO-247S
MBR30150PTS	150	30.0	0.95	15.0	50	150	TO-247S
MBR30200PTS	200	30.0	0.95	15.0	50	200	TO-247S
MBR4045PTS	45	40.0	0.65	20.0	200	45	TO-247S
MBR4060PTS	60	40.0	0.70	20.0	200	60	TO-247S
MBR40100PTS	100	40.0	0.85	20.0	50	100	TO-247S
MBR40150PTS	150	40.0	0.95	20.0	50	150	TO-247S
MBR40200PTS	200	40.0	0.95	20.0	50	200	TO-247S
MBR6045PTS	45	60.0	0.65	30.0	200	45	TO-247S
MBR6060PTS	60	60.0	0.80	30.0	200	60	TO-247S
MBR60100PTS	100	60.0	0.85	30.0	50	100	TO-247S
MBR60150PTS	150	60.0	0.95	30.0	50	150	TO-247S
MBR60200PTS	200	60.0	0.95	30.0	50	200	TO-247S
MBR3045PT	45	30.0	0.65	15.0	200	45	TO-247
MBR3060PT	60	30.0	0.70	15.0	200	60	TO-247
MBR30100PT	100	30.0	0.85	15.0	50	100	TO-247

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
MBR30150PT	150	30.0	0.95	15.0	50	150	TO-247
MBR30200PT	200	30.0	0.95	15.0	50	200	TO-247
MBR4045PT	45	40.0	0.65	20.0	200	45	TO-247
MBR4060PT	60	40.0	0.70	20.0	200	60	TO-247
MBR40100PT	100	40.0	0.85	20.0	50	100	TO-247
MBR40150PT	150	40.0	0.95	20.0	50	150	TO-247
MBR40200PT	200	40.0	0.95	20.0	50	200	TO-247
MBR6045PT	45	60.0	0.65	30.0	200	45	TO-247
MBR6060PT	60	60.0	0.80	30.0	200	60	TO-247
MBR60100PT	100	60.0	0.85	30.0	50	100	TO-247
MBR60150PT	150	60.0	0.95	30.0	50	150	TO-247
MBR60200PT	200	60.0	0.95	30.0	50	200	TO-247
JK1S240-45	45	240.0	0.70	120.0	500	45	SOT-227
JK2S240-45	45	240.0	0.70	120.0	500	45	SOT-227
SSL345A	45	3.0	0.45	3.0	300	45	SMA
TSSL310A	100	3.0	0.65	3.0	100	100	SMA
SSL545A	45	5.0	0.45	5.0	300	45	SMA
SSL56A	60	5.0	0.62	5.0	150	60	SMA
TSSL56A	60	5.0	0.62	5.0	100	60	SMA
TSSL510A	100	3.0	0.65	3.0	100	100	SMA
SSL345F	45	3.0	0.45	3.0	200	45	SMAF
TSSL310F	100	3.0	0.65	3.0	100	100	SMAF
SSL545F	45	5.0	0.45	5.0	300	45	SMAF
SSL56F	60	5.0	0.62	5.0	150	60	SMAF
TSSL56F	60	5.0	0.62	5.0	100	60	SMAF
TSSL510F	100	5.0	0.65	5.0	100	100	SMAF
SSL545B	45	5.0	0.45	5.0	300	45	SMB
SSL56B	60	5.0	0.62	5.0	150	60	SMB
TSSL56B	60	5.0	0.62	5.0	100	60	SMB
TSSL58B	80	5.0	0.63	5.0	100	80	SMB
TSSL510B	100	5.0	0.65	5.0	100	100	SMB
SSL545BF	45	5.0	0.45	5.0	300	45	SMBF
SSL56BF	60	5.0	0.62	5.0	150	60	SMBF
TSSL56BF	60	5.0	0.62	5.0	100	60	SMBF
TSSL58BF	80	5.0	0.63	5.0	100	80	SMBF
TSSL510BF	100	5.0	0.65	5.0	100	100	SMBF
TSSL58C	80	5.0	0.63	5.0	100	80	SMC
TSSL510C	100	5.0	0.65	5.0	100	100	SMC
SR545L	45	5.0	0.48	5.0	200	45	DO-27
SR560L	60	5.0	0.62	5.0	150	60	DO-27
TSR560L	60	5.0	0.62	5.0	100	60	DO-27

Schottky Diodes 肖特基二极管

Part Number	V _{RRM} (V)	I _O (A)	V _F (V)		I _R (μA)		Package
			Max.	I _F (A)	Max.	V _R (V)	
TSR5U60L	60	5.0	0.58	5.0	80	60	DO-27
TSR3100L	100	3.0	0.70	3.0	100	100	DO-27
TSR580L	80	5.0	0.63	5.0	100	80	DO-27
TSR5100L	100	3.0	0.65	5.0	100	100	DO-27
SBT10L100SCS	100	10.0	0.70	10.0	100	100	TO-252
SBT10L150SCS	150	10.0	0.85	10.0	50	150	TO-252
SBT20L45CT	45	20.0	0.52	10.0	200	45	TO-220AB
SBT30L45CT	45	30.0	0.53	15.0	300	45	TO-220AB
SBT40L45CT	45	40.0	0.53	20.0	300	45	TO-220AB
SBT20V60CT	60	20.0	0.60	10.0	150	60	TO-220AB
SBT30L60CT	60	30.0	0.60	15.0	300	60	TO-220AB
SBT40L60CT	60	40.0	0.60	20.0	300	60	TO-220AB
SBT20V80CT	80	20.0	0.63	10.0	120	80	TO-220AB
SBT30L80CT	80	30.0	0.65	15.0	200	80	TO-220AB
SBT40L80CT	80	40.0	0.65	20.0	200	80	TO-220AB
SBT10L100CT	100	10.0	0.73	5.0	100	100	TO-220AB
SBT20V100CT	100	20.0	0.70	10.0	100	100	TO-220AB
SBT30L100CT	100	30.0	0.73	15.0	200	100	TO-220AB
SBT40U100CT	100	40.0	0.70	20.0	200	100	TO-220AB
SBT20V120CT	120	20.0	0.85	10.0	100	120	TO-220AB
SBT30L120CT	120	30.0	0.92	15.0	100	120	TO-220AB
SBT20V150CT	150	20.0	1.15	10.0	50	150	TO-220AB
SBT30L150CT	150	30.0	1.25	15.0	50	150	TO-220AB
SBT40L150CT	150	40.0	0.86	20.0	50	150	TO-220AB
HBT20L200CT	200	20.0	0.90	10.0	2	200	TO-220AB
HBT30L200CT	200	30.0	0.90	15.0	2	200	TO-220AB
SBT20L45FCT	45	20.0	0.52	10.0	200	45	ITO-220AB
SBT30L45FCT	45	30.0	0.53	15.0	300	45	ITO-220AB
SBT40L45FCT	45	40.0	0.53	20.0	300	45	ITO-220AB
SBT20V60FCT	60	20.0	0.60	10.0	150	60	ITO-220AB
SBT30L60FCT	60	30.0	0.60	15.0	300	60	ITO-220AB
SBT40L60FCT	60	40.0	0.60	20.0	300	60	ITO-220AB
SBT20V80FCT	80	20.0	0.63	10.0	120	80	ITO-220AB
SBT30L80FCT	80	30.0	0.65	15.0	200	80	ITO-220AB
SBT40L80FCT	80	40.0	0.65	20.0	200	80	ITO-220AB
SBT10L100FCT	100	10.0	0.73	5.0	100	100	ITO-220AB
SBT20V100FCT	100	20.0	0.70	10.0	100	100	ITO-220AB
SBT30L100FCT	100	30.0	0.73	15.0	200	100	ITO-220AB
SBT40U100FCT	100	40.0	0.70	20.0	200	100	ITO-220AB
SBT20V120FCT	120	20.0	0.85	10.0	100	120	ITO-220AB
SBT30L120FCT	120	30.0	0.92	15.0	100	120	ITO-220AB

Schottky Diodes 肖特基二极管

Part Number	V_{RRM} (V)	I_O (A)	V_F (V)		I_R (μ A)		Package
			Max.	I_F (A)	Max.	V_R (V)	
SBT20V150FCT	150	20.0	1.15	10.0	50	150	ITO-220AB
SBT30L150FCT	150	30.0	1.25	15.0	50	150	ITO-220AB
SBT40L150FCT	150	40.0	0.86	20.0	50	150	ITO-220AB
HBT20L200FCT	200	20.0	0.90	10.0	2	200	ITO-220AB
HBT30L200FCT	200	30.0	0.90	15.0	2	200	ITO-220AB
SBT20L45DC	45	20.0	0.52	10.0	200	45	TO-263
SBT30L45DC	45	30.0	0.53	15.0	300	45	TO-263
SBT40L45DC	45	40.0	0.53	20.0	300	45	TO-263
SBT20V60DC	60	20.0	0.60	10.0	150	60	TO-263
SBT30L60DC	60	30.0	0.60	15.0	300	60	TO-263
SBT40L60DC	60	40.0	0.60	20.0	300	60	TO-263
SBT20V80DC	80	20.0	0.63	10.0	120	80	TO-263
SBT30L80DC	80	30.0	0.65	15.0	200	80	TO-263
SBT40L80DC	80	40.0	0.65	20.0	200	80	TO-263
SBT10L100DC	100	10.0	0.73	5.0	100	100	TO-263
SBT20V100DC	100	20.0	0.70	10.0	100	100	TO-263
SBT30L100DC	100	30.0	0.73	15.0	200	100	TO-263
SBT40U100DC	100	40.0	0.70	20.0	200	100	TO-263
SBT20V120DC	120	20.0	0.85	10.0	100	120	TO-263
SBT30L120DC	120	30.0	0.92	15.0	100	120	TO-263
SBT20V150DC	150	20.0	1.15	10.0	50	150	TO-263
SBT30L150DC	150	30.0	1.25	15.0	50	150	TO-263
SBT40L150DC	150	40.0	0.86	20.0	50	150	TO-263
HBT20L200DC	200	20.0	0.90	10.0	2	200	TO-263
HBT30L200DC	200	30.0	0.90	15.0	2	200	TO-263